

MSH4024D-L INVERTER / CHARGER

Introduction

The MSH4024D-L inverter/charger from Sensata Technologies – a pure sine wave inverter designed with true hybrid technology allowing it to run larger loads from smaller generators. Most inverters only use one source of energy to power loads, either from incoming AC power – shore or AC generator – or from the batteries. The MSH4024D-L combines the energy from both sources to power loads. This allows the inverter to recharge the batteries when there is surplus power or deliver more power to the loads if they require more than the AC input can supply by itself.



Features

- **Load Support** – Load support parallels the inverter output with incoming AC sources allowing it to run larger loads from smaller generators.
- **Battery Profile Presets** – Using the ME-RC-L or ME-ARC-L Remote Controls, easily choose from and set standard battery profiles, including Lithium Iron Phosphate (LFP), Gel, Flooded, AGM1, and AGM2.
- **Dual AC inputs** – The MSH4024D-L comes with two 60 amp AC inputs – a grid input at 60A and a generator input at 60A.
- **Pure sine wave** – Power your T.V.s, stereos, and other sensitive electronics without worry. The pure sine wave inverter and power factor corrected charger provides clean, reliable inverter power with low total harmonic distortion (THD) of less than 5%.
- **Accessible design** – The extra large AC access cover with terminal screw block and 360° DC connection terminals with covers make this inverter more accessible when it needs to be.
- **Interchangeable** – The MSH4024D-L is interchangeable with the Magnum MS Series and uses the same accessories as the MS Series.
- **Multiple ports** – The MSH4024D-L provides multiple ports, including an RS485 communication port for network expansion, and a remote port.
- **Convenient switches** – The MSH4024D-L comes with an on/off inverter-mounted switch with an easy-to-read LED indicator.
- **Buy with ease** – The MSH4024D-L is backed by a three-year (36-month) limited warranty.

Model Numbers

- MSH4024D-L

Available For

- Marine Systems
- RV Systems

Available Accessories

- Auto Generator Start - ME-AGS-N
- Battery Monitor Kit
- Conduit Box
- DC Load Disconnect
- Fuse Blocks
- MagWeb
- Remote - ME-ARC-L
- Remote - ME-RC-L
- Remote Switch Adapter
- RVC Bridge - ME-RVC-L
- Smart Battery Combiner



Pure Sine Wave



24 Battery Voltage Options



4000 VA Continuous Output Options



SPECIFICATIONS

	MSH4024D-L
INVERTER SPECIFICATIONS	
Input battery voltage range	18 - 34 VDC
Nominal AC output voltage	120 VAC $\pm$ 5%
Output frequency and accuracy	60 Hz $\pm$ 0.05 Hz
Total Harmonic Distortion (THD)	< 5%
1 msec surge current (amps AC)	120
100 msec surge current (amps AC)	82
5 sec surge power (real watts)	5800
30 sec surge power (real watts)	5400
5 min surge power (real watts)	4900
30 min surge power (real watts)	4500
Continuous power output at 25° C	4000 VA
Maximum continuous input current	267 ADC
Inverter efficiency (peak)	93.7%
Transfer time	< 16 msec
Search mode (typical)	< 7 watts
No load (120 VAC output, typical)	25 watts
Waveform	Pure Sine Wave
CHARGER SPECIFICATIONS	
Continuous output at 25° C	110 ADC
Charger efficiency	85%
Power factor	> .95
Input current at rated output (AC amps)	29
GENERAL FEATURES AND CAPABILITIES	
Transfer relay capability	60 AAC maximum each input
Five stage charging capability	Bulk, Absorb, Float, Equalize (requires remote), and Battery Saver™
Battery temperature compensation	Standard with available temp sensor connected (battery temp 0 - 50 °C)
Internal cooling	0 to 120 cfm variable speed drive using dual 92mm brushless DC fans
Overcurrent protection	Yes, with two overlapping circuits
Overtemperature protection	Yes on transformer, MOSFETS, and battery
Corrosion protection	Yes, PCB's conformal coated, powder coated chassis/top, and stainless steel fasteners
Dual AC branch rated output breakers	No
Listings	ETL listed to UL/cUL 458, CSA C22.2 No. 107.1-01
Warranty	Three years parts and labor

ENVIRONMENTAL SPECIFICATIONS	
Temperature (Operating/Non-operating)	-20° C to +60° C (-4° F to 140° F) to -40° C to +70° C (-40° F to 158° F)
Operating humidity	0 to 95% RH non-condensing
PHYSICAL SPECIFICATIONS	
Dimensions (l x w x h)	13.75" x 12.65" x 8.0" (34.9 cm x 32.1 cm x 20.3 cm)
Shipping dimensions (l x w x h)	19" x 17" x 13" (48.3 cm x 43.2 cm x 33 cm)
Mounting	Shelf or wall (vents not allowed to face downward unless ME-CB or MMP is installed)
Weight	58 lb (26.3 kg)
Shipping weight	63 lb (28.6 kg)
Max operating altitude	15,000' (4570 m)



GENERAL NOTES

Testing for specifications at 25° C.
Specifications subject to change without notice.



AGENCY APPROVALS & CERTIFICATIONS

- ETL listed to UL/cUL 458, CSA C22.2 No. 107.1-01

Sensata Technologies, Inc. ("Sensata") data sheets are solely intended to assist designers ("Buyers") who are developing systems that incorporate Sensata products (also referred to herein as "components"). Buyer understands and agrees that Buyer remains responsible for using its independent analysis, evaluation and judgment in designing Buyer's systems and products. Sensata data sheets have been created using standard laboratory conditions and engineering practices. Sensata has not conducted any testing other than that specifically described in the published documentation for a particular data sheet. Sensata may make corrections, enhancements, improvements and other changes to its data sheets or components without notice.

Buyers are authorized to use Sensata data sheets with the Sensata component(s) identified in each particular data sheet. HOWEVER, NO OTHER LICENSE, EXPRESS OR IMPLIED, BY ESTOPPEL OR OTHERWISE TO ANY OTHER SENSATA INTELLECTUAL PROPERTY RIGHT, AND NO LICENSE TO ANY THIRD PARTY TECHNOLOGY OR INTELLECTUAL PROPERTY RIGHT, IS GRANTED HEREIN. SENSATA DATA SHEETS ARE PROVIDED "AS IS". SENSATA MAKES NO WARRANTIES OR REPRESENTATIONS WITH REGARD TO THE DATA SHEETS OR USE OF THE DATA SHEETS, EXPRESS, IMPLIED OR STATUTORY, INCLUDING ACCURACY OR COMPLETENESS. SENSATA DISCLAIMS ANY WARRANTY OF TITLE AND ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, QUIET ENJOYMENT, QUIET POSSESSION, AND NON-INFRINGEMENT OF ANY THIRD PARTY INTELLECTUAL PROPERTY RIGHTS WITH REGARD TO SENSATA DATA SHEETS OR USE THEREOF.

All products are sold subject to Sensata's terms and conditions of sale supplied at www.sensata.com SENSATA ASSUMES NO LIABILITY FOR APPLICATIONS ASSISTANCE OR THE DESIGN OF BUYERS' PRODUCTS. BUYER ACKNOWLEDGES AND AGREES THAT IT IS SOLELY RESPONSIBLE FOR COMPLIANCE WITH ALL LEGAL, REGULATORY AND SAFETY-RELATED REQUIREMENTS CONCERNING ITS PRODUCTS, AND ANY USE OF SENSATA COMPONENTS IN ITS APPLICATIONS, NOTWITHSTANDING ANY APPLICATIONS-RELATED INFORMATION OR SUPPORT THAT MAY BE PROVIDED BY SENSATA.

Mailing Address: Sensata Technologies, Inc., 529 Pleasant Street, Attleboro, MA 02703, USA.

CONTACT US

651-653-7000
800-553-6418
InverterInfo@sensata.com

Power Conversion
www.magnum-dimensions.com



This manual is provided courtesy of **RV Tech Cheat Sheet**



Professional resources for the whole RV industry — free.

We put manuals, wiring diagrams and hard-won tech knowledge in every technician's hands, so repairs get done right the first time, techs work faster, and RV owners everywhere get better service.



rvtechcheatsheet.com/manuals

Find thousands more RV manuals, wiring diagrams and parts lists

RV techs: share fixes, ask questions and learn from each other.

Join our free Facebook group →



Follow proper safety practices. If in doubt, consult a professional RV technician.