



20A /40A DC-DC Batterie Ladegerät



RENOGY 20A /40A DC-DC Batterie Ladegerät

Mit dem Renogy DC-DC Ladegerät wird Ihre Housebatterie während der Fahrt immer von der Starterbatterie aufgeladen. Es ist ideal für RV; Boot oder andere natzunabhängige Fahrzeuge.

Modell #	Eingangsspannung	Ladespannung	Ampere	Dimension	Gewicht
DCC1212-20	8V-16V	13.2V - 14.7V	20A	21,1x17,5x 6,8 cm	1,3kg
DCC1212-40	8V-16V	13.2V - 14.7V	40A	26,1x 17,5x 6,8 cm	1,8kg



SPEZIFIKATIONEN

Modell	DCC 1212-20	DCC 1212-40
Transformation	12V-12v	
Nenneingangsspannung	12V~	
Ausgangsspannung	8V-16V	
Ladestrom	20A	40A
Ladespannung	13.2V-14.7	
Ausgang	250W	500W
Restwelligkeit Ausgangsspannung bei Nennstrom	<50 mVeff	
Effizienz bis zu	90%	
Selbstverbrauch	<0.4A	
Betriebstemperatur	-20°C bis +50°C	
Feuchtigkeit	<95%Non-condensing	
Dimension (W x D X H)	21,1x17,5 x 6,8 cm	26,1x 17,5 x 6,8 cm
Gewicht	1,3kg	1,8kg
Zertifikation	CE	





This manual is provided courtesy of **RV Tech Cheat Sheet**



Professional resources for the whole RV industry — free.

We put manuals, wiring diagrams and hard-won tech knowledge in every technician's hands, so repairs get done right the first time, techs work faster, and RV owners everywhere get better service.



rvtechcheatsheet.com/manuals

Find thousands more RV manuals, wiring diagrams and parts lists

RV techs: share fixes, ask questions and learn from each other.

Join our free Facebook group →



Follow proper safety practices. If in doubt, consult a professional RV technician.