

PROsine 2.0

INVERTER/CHARGER

xantrex™
Smart choice for power™

Heavy duty, true sine wave inverters!

Available in:

12 V

24 V



A powerful all-in-one solution, PROsine 2.0 inverter/chargers deliver up to 2000 watts of unsurpassed clean true sine wave output power and combines this with a 100 amp, multistage battery charger. Series stackability allows for two units to power 240 VAC applications such as power tools, over ranges, washer/ dryer combinations and air conditioner. The system includes a full function LCD remote control panel and battery temperature sensor.

Product Features

- » 2000-watt inverter (4500-watt surge)
- » 100 A power factor corrected multistage charger
- » True sine wave output (crystal controlled)
- » Built-in 30 A transfer switch automatically transfers between inverter power and incoming AC power
- » Series stackability for 120/240 VAC (requires two units)
- » Power sharing reduces charging current when AC loads are activated to prevent tripping of shorepower breaker
- » Equalization mode conditions batteries for longer life
- » Optional GFCI version available
- » LCD remote control panel and temperature sensor included
- » Compact, lightweight, and easy to install
- » Two year warranty

Remote Control Panel included (24-month warranty)

- » Independent inverter and charger on/off controls
- » Push button control of power sharing, equalizing, battery set-up, and system configuration
- » Easy to read backlit digital text messaging display
- » Numerically displays AC and DC system information including volts, amps and state of inverter/charger
- » Monitors battery temperature and adjusts charger to provide an accurate charge in any climate

Protection Features

- » Over voltage and under voltage protection
- » Over temperature and automatic overload protection
- » Short circuit AC backfeed protection
- » Approved to the UL 458 regulatory standard

Applications:



Recreational vehicles



Marine



Heavy duty trucks



Work vehicles



Buses / coaches



Specialty vehicles



CSA/NRTL certified to UL and CSA standards



Schneider Electric Solar Business

3700 Gilmore Way
Burnaby, British Columbia
Canada V5A 4B5
800 670 0707 Toll Free
604 420 1591 Fax

541 Roske Drive, Suite A
Elkhart, Indiana
USA 46516
800 446 6180 Toll Free
574 294 5989 Fax

www.xantrex.com

PROsine 2.0

INVERTER/CHARGER



Electrical specifications - Inverter

Output power continuous	2000 watts
Surge rating (5 sec.)	4.5 kW
Output current	17 A RMS continuous, 50 A peak
Output voltage	117 VAC RMS
Output frequency	60 Hz +/-0.05% (crystal controlled)
Output waveform	True sine wave <2% THD typical
Efficiency (full load)	87%
Peak efficiency	89%
No load power draw (inverting)	<25 W
No load power draw (search mode, 3 s interval)	<2 W
Input DC voltage range	10 – 16 VDC

Electrical specifications - Charger

Output current	100 A DC continuous
Output voltage	12 VDC nominal
Output voltage range	0 – 17.5 V
Charge control	3 stage with manual equalize
Charge temperature compensation	Remote battery sensor
Efficiency	81% typical
AC input power factor	0.99
Input current (for 100 A charging)	15 A RMS nominal
Input AC voltage	120 VAC nominal
Input AC voltage range	90 – 135 VAC

General Specifications

Compatible battery types	Flooded / gel / AGM / Pb-Ca
Transfer relay rating	30 A, 1.5 HP, 120 VAC
Transfer time (AC to inverter and inverter to AC)	16 ms typical
Storage ambient temperature range	-40°F – 158°F (40°C – 70°C)
Optimal operating temperature range	32°F – 104°F (0°C – 40°C)
Operating ambient temperature range	-4°F – 140°F (-20°C – 60°C - derated above 40°C)
Dimensions (HxWxD)	17.7 x 11.2 x 5.7" (450 x 285 x 145 mm)
Weight	24.0 lb (11 kg)
Warranty	2 years
Part number	805-200 (Hardwire) 805-2020 (Hardwire & GFCI) 808-2000 (DC wiring box)

Regulatory Approvals

CSA/NRTL certified to CSA 107.1, UL 458 (including Marine supplement)

KKK-A-1822D compliant, for use in "Star-of-Life" ambulances (GFCI version)

ABCY compliant, recommended practices E-8, E-9, A-20, and A-25 for marine use

Note: Specifications subject to change without notice.



This manual is provided courtesy of **RV Tech Cheat Sheet**



Professional resources for the whole RV industry — free.

We put manuals, wiring diagrams and hard-won tech knowledge in every technician's hands, so repairs get done right the first time, techs work faster, and RV owners everywhere get better service.



rvtechcheatsheet.com/manuals

Find thousands more RV manuals, wiring diagrams and parts lists

RV techs: share fixes, ask questions and learn from each other.

Join our free Facebook group →



Follow proper safety practices. If in doubt, consult a professional RV technician.