

LIPPERT
COMPONENTS®

ELECTRIC STABILIZER MOTOR COMPARATIVE

QR-041

LEVELING AND STABILIZATION

This switch-to-motor comparative information applies to stabilizers only and shall not be used as a resource for any leveling jacks or leveling operation.

Using the Motor Wire-to-Switch Wire Chart

1. Find motor in Motor column.
2. Find wire color in Motor Wire Color column.
3. Follow Motor Wire Color across the row to find its Function, Switch Wire Color and applicable Switch Part#.

Example: Klauber #[138445](#) > Black motor wire > Retract function > Yellow switch wire > Switch #387874. Connect the Klauber motor's Black wire to the Yellow switch wire on [387874](#) switch to complete the Retract function circuit.

Motor Wire-to-Switch Wire Chart				
Motor	Motor Wire Color	Function	Switch Wire Color	Switch Part#
Klauber (Part# 138445) <i>Ultra Light Stabilizer</i>	Black	Retract	Yellow	138415 242409 344484 387874
			Black	144214
	White	Extend	Blue	138415 242409 344484 387874
			Green	144214
Wuyi (Part# 138445) <i>Ultra Light Stabilizer</i>	Black	Retract	Black	144214
			Yellow	242409 387874
	Red	Extend	Green	144214
			Blue	242409 387874
Prabha and Yaoou (Part# 352338) <i>High Speed Stabilizer (yellow arms)</i>	Black	Retract	Yellow	138415 242409 344484 387874
			Black	144214
	Red	Extend	Blue	138415 242409 344484 387874
			Green	144214

As a supplier of components to the RV industry, safety, education and customer satisfaction are our primary concerns. Should you have any questions, please do not hesitate to contact us at (574) 537-8900 or by email at customerservice@lci1.com. Self-help tips, technical documents, product videos and a training class schedule are available at lci1.com or by downloading the MyLCI app.



This manual is provided courtesy of **RV Tech Cheat Sheet**



Professional resources for the whole RV industry — free.

We put manuals, wiring diagrams and hard-won tech knowledge in every technician's hands, so repairs get done right the first time, techs work faster, and RV owners everywhere get better service.



rvtechcheatsheet.com/manuals

Find thousands more RV manuals, wiring diagrams and parts lists

RV techs: share fixes, ask questions and learn from each other.

Join our free Facebook group →



Follow proper safety practices. If in doubt, consult a professional RV technician.