

WF-5110RS

1000 Watt Inverter



THE HEARTBEAT OF TODAY'S RVs

Model WF-5110RS

Output: 120VAC
Pure Sine Wave,
60 Hz, 1000W
Input: 10-15 VDC




Improved Battery Longevity

WFCO's WF-5110RS is the new and improved 1000-watt inverter in our product line. The new design reduces parasitic draw, while maximizing battery power and efficiency. Additionally, the WF-5110RS still maintains the reverse polarity protection in the event that batteries are hooked up backwards and the automatic transfer system of AC input to bypass when required. WFCO's WF-5110RS improved upon the same reliable inverter that customers have come to love, with the added benefit of a longer lasting battery that customers need.

With over a decade of inverter manufacturing, WFCO knows what is important. Reliability, clean signal, easy installation, and intelligent power management make the WF-5110RS the best choice RV inverter.

Reliability. Vertically integrated, WFCO has total supply chain control, ensuring quality materials, parts and processes at each stage. Components are quality tested at critical manufacturing stages resulting in zero faults at the final 4-hour burn-in test, helping keep warranty claims below 1%. All models are UL® and cUL® listed and FCC Class B compliant.

PRODUCT FEATURES



Three status indicators, a voltage indicator with a message panel and selection button communicate useful information to the owner or technician:

- Amber: Indicates unit is in invert mode (the inverter is creating 120V power).
- Green: Indicates AC input status.
- Red: Indicates inverter fault status.
- LCD Message Panel: Indicates operation status.
- Selection Button lets user choose screens on the display: Battery input voltage, AC output Amps and voltage.



Circuit Breaker to protect outlet from shore power shorts and overloads.

Other features:

- Remote control.
- Built-in circuit protection on the DC side.
- Pure sine wave output with THD <3%.
- Built in <50 millisecond transfer time. This allows the transfer from utility power to inverter power to be interruption free, protecting sensitive equipment.

WF-5110RS

EASY INSTALLATION

All WFCO models are designed with the installer and assembly line in mind. We work with installers every day to find ways to streamline installation to reduce time and fiddle factor.



The WF-5110RS features a time-saving plug-and-play design that allows it to be simply plugged into an AC outlet to connect directly to the RV's AC system.



The WF-5110RS remote includes an ON/OFF button and a 20-ft. cable. The switch on the face of the inverter must be in the "out" position for the remote to work.



The WF-5110RS allows manufacturers the use of more cost effective 4-gauge wiring versus the 2-gauge wire specified by competitors.



No crimping required for 4-gauge wire terminal connections, reducing installation time and fatigue.

SPECIFICATIONS

WF-5110RS

Power Output	1000W
Input Voltage	10.7 - 16VDC
Output Waveform	Pure Sine Wave
Voltage Output	120VAC / 60 Hz
Efficiency Load	>86% at Full Load
Transfer Switch	8.5 A
Transfer Time	20 milliseconds
AC Output Breaker	12 A
Dimensions	11"W x 3.9"H x 14.6"D
Weight	11.72 lb

Certifications: UL® and cUL® listed and FCC Class B compliant.
Specifications are subject to change without notice or obligation.

ALL MODELS:

Standard Safety Features/Protections:
Overload, Short Circuit, Over/Under Input
Voltage, Over Temperature, Automatically
Resettable Reverse Polarity Protection,
AC Output Breaker



THE HEARTBEAT OF TODAY'S RVs
2021 Aeroplex Drive North · Elkhart, IN 46514
P- 877.294.8997 · F- 574.294.8698
wfcoelectronics.com

AD-BSI-0001-0 © 2016 WFCO Electronics Printed in USA 08/16

The RV
Industry's
Electrical
Authority

Our Power Pros provide expert
technical support for everything
the RV industry needs. Visit
wfcoelectronics.com/support.



EXPERT PRODUCT SUPPORT



This manual is provided courtesy of **RV Tech Cheat Sheet**



Professional resources for the whole RV industry — free.

We put manuals, wiring diagrams and hard-won tech knowledge in every technician's hands, so repairs get done right the first time, techs work faster, and RV owners everywhere get better service.



rvtechcheatsheet.com/manuals

Find thousands more RV manuals, wiring diagrams and parts lists

RV techs: share fixes, ask questions and learn from each other.

Join our free Facebook group →



Follow proper safety practices. If in doubt, consult a professional RV technician.