


WF-8500 MBA Series

Replacements for 40/60 Amp Power Centers



THE HEARTBEAT OF TODAY'S RVs



Model WF-8540-MBA

Output: 40 Amps DC
Input: 105-130 VAC,
60 Hz, 685W

Model WF-8560-MBA

Output: 60 Amps DC
Input: 105-130 VAC,
60 Hz, 1030W

Easy Installation

With 40 years of power equipment experience, WFCO knows what is important to our customers. High on the list is easy, fast installation. Our WF-8500-MBA Series is a quick, easy replacement part for all power centers. It installs easily with only two screws, three AC wires, and two DC wires. With no need to re-wire, installation is only 10 minutes! Customers also have the option for Reverse Polarity Detection that meets new RVIA & NEC requirements with an audible alarm notification. No additional wiring or hookup required and accepts hi-pot testing.

SMART ENGINEERING: THREE-STAGE CHARGING IS BETTER

WFCO's automatic three-stage converter handles every charging need for the RV while extending the battery's life. Well-maintained batteries should never need more than two-stage (Normal and Trickle) charging. Our third stage (Bulk) is provided for the rare times a battery needs extra-power for charging. See wfcoelectronics.com for details.



PRODUCT FEATURES

SPECIFICATIONS	WF-8540-MBA	WF-8560-MBA
Power Input	685W	1030W
Input Voltage	105-130 VAC/60 Hz	105-130 VAC/60 Hz
Output Current	40A	60A
Converter Type	3 Stage Converter Charger	
Voltage Output	13.2 - 14.4 VDC	
Normal mode	13.6 VDC	
Trickle charge mode	13.2 VDC	
Bulk charge mode	14.4 VDC	
Dimensions	7 1/16"W x 3 7/8"H x 9 1/2"D	
Weight	4 lbs.	5 lbs.

Certifications: UL* and cUL* listed and FCC Class B compliant. Specifications are subject to change without notice or obligation.

ALL MODELS: Standard Safety Features/Protections: Over Current, Over Temperature, Over Voltage, Reverse Polarity



THE HEARTBEAT OF TODAY'S RVs
2021 Aeroplex Drive North · Elkhart, IN 46514
P- 877.294.8997 · F- 574.294.8698
wfcoelectronics.com

AD-BSC-0014-0 © 2016 WFCO Electronics Printed in USA 07/16

The RV
Industry's
Electrical
Authority

Our Power Pros provide expert
technical support for everything
the RV industry needs. Visit
wfcoelectronics.com/support.





This manual is provided courtesy of **RV Tech Cheat Sheet**



Professional resources for the whole RV industry — free.

We put manuals, wiring diagrams and hard-won tech knowledge in every technician's hands, so repairs get done right the first time, techs work faster, and RV owners everywhere get better service.



rvtechcheatsheet.com/manuals

Find thousands more RV manuals, wiring diagrams and parts lists

RV techs: share fixes, ask questions and learn from each other.

Join our free Facebook group →



Follow proper safety practices. If in doubt, consult a professional RV technician.